

AMENDMENTS TO THE CLAIMS:

This listing of claims will replace all prior versions, and listings, of claims in the application.

LISTING OF CLAIMS:

1. (Original) A radio frequency modulator, comprising:
a phase lock loop (PLL) having an input port for receiving a modulation signal and producing as an output signal a modulated RF signal at an output port;
a phase demodulator having an input port for receiving the modulated RF signal and having an output port for providing a phase information signal;
a comparator having a first input port for receiving the phase information signal and a second input port for receiving the modulation signal and an output port for providing an error signal; and
a pre-emphasis filter in response to receiving the error signal adjusts the modulation signal provided to the PLL.
2. (Original) A radio frequency modulator as defined in claim 1, wherein the pre-emphasis filter comprises a digital pre-emphasis filter.
3. (Original) A radio frequency modulator as defined in claim 1, further comprising a direct digital synthesizer (DDS) coupled between the pre-emphasis filter and the PLL.

4. (Original) A radio frequency modulator as defined in claim 1, wherein the PLL has a transfer function and the pre-emphasis filter preconditions the modulation signal with a filter response which is about the inverse of the PLL transfer function.

5. (Original) A radio frequency modulator as defined in claim 1, wherein the phase demodulator comprises a digital phase demodulator.

6. (Original) A radio frequency modulator as defined in claim 1, wherein the modulation signal comprises a digital modulation signal.

7. (Original) A method of producing a stable and low noise modulator, comprising the steps of:

- (a) providing a phase lock loop (PLL) for receiving a modulation signal and producing a modulated RF signal;
- (b) demodulating the modulated RF signal to produce a demodulated signal;
- (c) comparing the demodulated signal with the modulation signal in order to provide an error signal; and
- (d) using the error signal to precondition the modulation signal provided to the PLL using a pre-emphasis filter.

8. (Original) A method as defined in claim 7, wherein step (d) comprises preconditioning the modulation signal in the digital domain using a digital pre-emphasis filter.

9. (Original) A method as define in claim 7, wherein the PLL has a transfer function and the pre-emphasis filter has a filter response of about the inverse of the PLL transfer function.

10-21. (Canceled).

21. (Currently amended) A digital modulator for use in a radio frequency transmitter, comprising:

a phase-lock-loop (PLL) loop producing as an output signal a modulated RF signal, wherein the phase lock loop (PLL) comprises a loop filter coupling a phase/frequency detector to an oscillator;

a phase demodulator having an input port for receiving unmodified the modulated RF signal and having an output port for providing a phase information signal; and

a comparator having a first input port for receiving the phase information signal and having an output port for outputting an error signal.

22. (Previously presented) A radio frequency modulator as defined in claim 1, wherein the modulation signal is subject to a phase delay prior to being input to the second input port of the comparator.

23. (Previously presented) A radio frequency modulator as defined in claim 1, wherein the phase lock loop (PLL) comprises a loop filter coupling a phase/frequency detector and charge pump to an oscillator.

24. (Previously presented) A radio frequency modulator as defined in claim 23, wherein the loop filter is a low pass filter.

25. (Previously presented) A radio frequency modulator as defined in claim 23, wherein the oscillator is a voltage controlled oscillator (VCO).

26. (Currently amended) A radio frequency (RF) modulator comprising:
a phase-lock-loop (PLL) ~~loop~~ including a loop filter and receiving as an input signal a modulation signal and producing as an output signal a modulated RF signal;
first circuitry for receiving unmodified the modulated RF signal and outputting an error signal; and
second circuitry responsive to said error signal for controlling the amplitude of the modulation signal.

27. (Previously presented) The radio frequency (RF) modulator of claim 26, wherein said circuitry for receiving unmodified the modulated RF signal and outputting an error signal comprises a phase demodulator coupled to receive the modulated RF signal.

28. (Previously presented) The radio frequency (RF) modulator of claim 27, wherein said circuitry for receiving unmodified the modulated RF signal and outputting an error signal further comprises a comparison circuit coupled to the phase demodulator.

29. (Previously presented) A method of producing phase shifts in a modulated RF signal, comprising the steps of:
producing a modulated RF signal;
receiving unmodified the modulated RF signal and outputting an error signal;
and
controlling the amplitude of a modulation signal in response to the error signal.

30. (Previously presented) The method of claim 29, further comprising preconditioning the modulation signal in the digital domain prior to injection into a phase lock loop.

31. (Previously presented) The method of Claim 30, wherein a pre-emphasis filter is used in preconditioning the modulation signal.